



XP13000HX

DUAL FUEL PORTABLE GENERATOR

13,000 STARTING WATTS • 10,500 RUNNING WATTS



FEATURING CO ALERT TECHNOLOGY





XP13000HX

DUAL FUEL PORTABLE GENERATOR


FEATURES

- Large Fuel Tank
- All Metal Construction
- Powerful OHV Engine
- All-Copper Windings
- Digital Command Center
- Fully-Loaded Power Panel
- Push Button Start
- Low Oil Sensor



CO ALERT TECHNOLOGY

OUTLETS



X4
120V 20A
GFCI Outlet



X1
120V 30A
Twist Lock



X1
120/240V 30A
Twist Lock



X1
120/240V 50A
Heavy Duty Outlet

SPECS

Watts (Gasoline)	13,000 (peak) • 10,500 (running)
Watts (Propane)	12,350 (peak) • 9,975 (running)
Engine	OHV 500cc
Amperage	87.50A / 43.75A
Voltage	120V / 240VAC
Fuel Type	Gasoline / Propane
Runtime (Gasoline) at 50% Load	8.5 hrs
Runtime (Propane) at 50% Load	6.5 hrs